

WALLENSTEIN

BY: EMB MFG INC.

POWERED by
HONDA™



EC2600



HUF12000E



GF6000EA
with optional WK210 Wheel Kit

GENERATORS

www.embmfg.com

EC SERIES



WK210 & WK213
(OPTIONAL)
Wheel Kits Fit All
Models
WK210 - 10" Tires
WK213 - 13" Tires



EC2600



EC2500

- **ECONOMY**
- **ROLL CAGE FRAME**
- **OIL ALERT™**
- **20A TEE RECEPTACLES**
- **REAR MOUNTED ELECTRICAL PANEL**



EC3300



EC5000

MODEL	EC2500	EC2600	EC3300	EC5000
ENGINE	5 HP / GC160	5.5 HP / GX160	6.5 HP / GX200	9 HP / GX270
MAXIMUM WATTS	2500	2600	3300	5000
CONTINUOUS WATTS	2100	2300	3000	4500
MAXIMUM AMPS (120V / 240V)	20.8	21.6	27.5	41.6 / 20.8
CONTINUOUS AMPS	17.5	19	25	37.5 / 18.8
FREQUENCY	60 HZ	60 HZ	60 HZ	60 HZ
VOLTAGE	120V	120V	120V	120 / 240V
FUEL TANK CAPACITY	2 LITRES	3.7 LITRES	3.7 LITRES	6 LITRES
RUN TIME (HOURS)	HALF LOAD FULL LOAD	3 2.5	4 3	4 3
WEIGHT (LBS)	68	74	85	122
DIMENSIONS (INCHES)	LENGTH WIDTH HEIGHT	22 16 16	22 16 16	25.5 20 21
OIL ALERT SYSTEM	YES	YES	YES	YES
OVERLOAD PROTECTION	YES	YES	YES	YES
ENGINE STARTING	RECOIL	RECOIL	RECOIL	RECOIL
AUTO IDLE WITH IDLE DELAY	N / A	N / A	N / A	N / A
HOURLY METER	N / A	N / A	N / A	N / A

EU SERIES



EU7200E

- OIL ALERT™
- FOUR 120V 20A TEE OUTLETS
- ONE 120V TWIST LOCK (L305)
- ONE 120 / 240V TWIST LOCK (L14-30)
- KEY SWITCH AND CHOKE IN CONTROL PANEL ON ELECTRIC START MODELS
- ELECTRIC START MODELS ACCEPT STANDARD L & G BATTERIES



EU SERIES CONTROL PANEL AND ELECTRICAL OUTLETS




EU5000

WK210 & WK213
(OPTIONAL)

Wheel Kits Fit All
Models

WK210 - 10" Tires
WK213 - 13" Tires



MODEL		EU5000	EU5000E	EU6000	EU6000E	EU7200E
ENGINE		9 HP / GX270	9 HP / GX270	11 HP / GX340	11 HP / GX340	13 HP / GX390
MAXIMUM WATTS		5000	5000	6000	6000	7200
CONTINUOUS WATTS		4500	4500	5000	5000	6500
MAXIMUM AMPS (120V / 240V)		41.6 / 20.8	41.6 / 20.8	55 / 27.5	55 / 27.5	60 / 30
CONTINUOUS AMPS		37.5 / 18.8	37.7 / 18.8	41.6 / 20.8	41.6 / 20.8	54.1 / 27.1
FREQUENCY		60 HZ	60 HZ	60 HZ	60 HZ	60 HZ
VOLTAGE		120 / 240V	120 / 240V	120 / 240V	120 / 240V	120 / 240V
FUEL TANK CAPACITY		21 LITRES	21 LITRES	21 LITRES	21 LITRES	21 LITRES
RUN TIME (HOURS)	HALF LOAD FULL LOAD	12 7	12 7	12 7	12 7	11.5 6.5
WEIGHT (LBS)		159	163	186	189	208
DIMENSIONS (INCHES)	LENGTH WIDTH HEIGHT	28 20 24	28 20 24	28 20 24	28 20 24	28 20 24
OIL ALERT SYSTEM		YES	YES	YES	YES	YES
OVERLOAD PROTECTION		YES	YES	YES	YES	YES
ENGINE STARTING		RECOIL	REC. / ELECTRIC	RECOIL	REC. / ELECTRIC	REC. / ELECTRIC
AUTO IDLE WITH IDLE DELAY		N/A	N/A	N/A	N/A	N/A
HOUR METER		N/A	N/A	N/A	N/A	N/A

GF SERIES

RENTAL & CONSTRUCTION



GF SERIES CONTROL PANEL AND ELECTRICAL OUTLETS

- **AUTO IDLE WITH VARIABLE TIME DELAY AND HOUR METER**
- **OIL ALERT™**
- **FOUR 120V GFI OUTLETS**
- **ONE 120V TWIST LOCK (L305)**
- **ONE 120 / 240V TWIST LOCK (L14-30)**
- **KEY SWITCH AND CHOKE IN CONTROL PANEL ON ELECTRIC START MODELS**
- **ELECTRIC START MODELS ACCEPT STANDARD L & G BATTERIES IN FRAME**

WK210 &
WK213
(OPTIONAL)
Wheel Kits Fit
All Models
WK210 - 10" Tires
WK213 - 13" Tires



GF5000A



GF6000A



GF7200EA

MODEL	GF5000A	GF5000EA	GF6000A	GF6000EA	GF7200EA
ENGINE	9 HP / GX270	9 HP / GX270	11 HP / GX340	11 HP / GX340	13 HP / GX390
MAXIMUM WATTS	5000	5000	6000	6000	7200
CONTINUOUS WATTS	4500	4500	5000	5000	6500
MAXIMUM AMPS (120V / 240V)	41.6 / 20.8	41.6 / 20.8	55 / 27.5	55 / 27.5	60 / 30
CONTINUOUS AMPS	37.5 / 18.8	37.7 / 18.8	41.6 / 20.8	41.6 / 20.8	54.1 / 27.1
FREQUENCY	60 HZ	60 HZ	60 HZ	60 HZ	60 HZ
VOLTAGE	120 / 240V	120 / 240V	120 / 240V	120 / 240V	120 / 240V
FUEL TANK CAPACITY	21 LITRES	21 LITRES	21 LITRES	21 LITRES	21 LITRES
RUN TIME (HOURS)					
HALF LOAD	12	12	12	12	11.5
FULL LOAD	7	7	7	7	6.5
WEIGHT (LBS)	159	163	186	189	208
DIMENSIONS (INCHES)					
LENGTH	28	28	28	28	28
WIDTH	20	20	20	20	20
HEIGHT	24	24	24	24	24
OIL ALERT SYSTEM	YES	YES	YES	YES	YES
OVERLOAD PROTECTION	YES	YES	YES	YES	YES
ENGINE STARTING	RECOIL	REC. / ELECTRIC	RECOIL	REC. / ELECTRIC	REC. / ELECTRIC
AUTO IDLE WITH IDLE DELAY	YES	YES	YES	YES	YES
HOUR METER	YES	YES	YES	YES	YES

WELDER/GENERATORS



WDC160



WDC190EA
(Shown with optional
WK213 wheel kit.
Battery not included.)



WDC190EA PANEL

- **60% DUTY CYCLE**
- **WELDING HELMET INCLUDED**
- **25' CABLES**

MODEL		WDC160	WDC190E	WDC190EA
ENGINE		11 HP / GX340	13 HP / GX390	13 HP / GX390
FUEL TANK CAPACITY		6.5 LITRES	6.8 LITRES	21 LITRES
RUN TIME	HALF LOAD (HOURS)	4	3.5	12
	FULL LOAD (HOURS)	3	2.75	7
OIL ALERT SYSTEM		YES	YES	YES
OVERLOAD PROTECTION		YES	YES	YES
ENGINE STARTING		RECOIL	RECOIL / ELECTRIC	RECOIL / ELECTRIC
AUTO IDLE WITH IDLE DELAY		N/A	N/A	YES
HOUR METER		N/A	N/A	YES
GENERATOR SPECIFICATIONS				
MAXIMUM WATTS		3500	3500	3500
CONTINUOUS AMPS		3000	3000	3000
MAXIMUM AMPS (120V / 240 V)		15 / 30	15 / 30	15 / 30
CONTINUOUS AMPS		12.5 / 25	12.5 / 25	12.5 / 25
FREQUENCY		60 HZ	60 HZ	60 HZ
VOLTAGE		120 / 240	120 / 240	120 / 240
WELDER SPECIFICATIONS				
MAXIMUM AMPS (DC)		160	190	190
DUTY CYCLE		60%	60%	60%
CABLE LENGTH		25 FT.	25 FT.	25 FT.
HELMET		INCLUDED	INCLUDED	INCLUDED
WEIGHT		183 LBS	197 LBS	213 LBS
DIMENSIONS (INCHES)	LENGTH	28	28	28
	WIDTH	20	20	20
	HEIGHT	21	21	28

HUF SERIES



HUF12000E



HUF12000EA



WK210 & WK213
(OPTIONAL)
Wheel Kits Fit All Models
WK210 - 10" Tires
WK213 - 13" Tires

Battery not included.

MODEL		HUF12000E	HUF12000EA
ENGINE		20 HP / GX620	20 HP / GX620
MAXIMUM WATTS		12000	12000
CONTINUOUS WATTS		10000	10000
MAXIMUM AMPS (120V / 240V)		50 / 100	50 / 100
CONTINUOUS AMPS		42/84	42/84
FREQUENCY		60 HZ	60 HZ
VOLTAGE		120 / 240	12 / 240
FUEL TANK CAPACITY		40 LITRES	40 LITRES
RUN TIME (HOURS)	HALF LOAD FULL LOAD	10 7	10 7
WEIGHT (LBS)		348	348
DIMENSIONS (INCHES)	LENGTH WIDTH HEIGHT	32 22 29	32 22 29
OVERLOAD PROTECTION		YES	YES
ENGINE STARTING		ELECTRIC	ELECTRIC
AUTO IDLE WITH IDLE DELAY		NO	YES
HOUR METER		YES	YES
GFI RECEPTACLES		NO	YES
VOLTAGE METER		YES	YES

Available At:

EMB MFG. INC.
4144 Boomer Line,
St. Clements, ON N0B 2M0
Phone: 519-699-9283 Fax: 519-699-4146
www.embmfg.com sales@embmfg.com